

Solar Powered Fountain Materials List


2 solar panels

1 shallow tray

1 pump

3 tubes

1 book
My Light




Solar Powered Water Fountain

Ages: Kindergarten & up

Transform solar energy into electricity!

The electricity generated by the solar panel can power a water pump. Use Play-doh or clay to create a 3D water fountain.


Extension activities included: Experiment with different light sources, solar panel configuration, and the intensity and angle of the light source to determine which design powers the water pump best. Test different tube sizes to explore the effect on water flow.



Donated by the Center for the Advancement of Sustainable Energy



Thank you for choosing this
Resource Kit from
the Center for the Advancement of
Sustainable Energy.



NOTE: Please dry all materials thoroughly before returning.



Setting up the solar fountain

https://www.youtube.com/watch?v=67IBTUZF3_k



TedEd: How solar panels work?

<https://www.youtube.com/watch?v=xKxrkt7CpY&t=193s>



KidWind Renewable Energy Challenge

<https://www.youtube.com/watch?v=n9rR9NH81Y>

Contact Information



case@jmu.edu www.jmu.edu/case


Kits available from




Exploring Wind Energy




Exploring Solar Energy



Wind Powered Light (Firefly)



Solar Powered Water Fountain



Educator Kit: Wind Energy




Educator Kit: Solar Energy





Solar Fountain Activity



Grades

- 2-12

Concepts

- Inquiry and Science Process
- Energy and Energy Transfer
- Forces and Motion
- Earth Science
- Engineering, Art, and Design
- Using Basic Tools
- Collecting and Interpreting Data

Disciplinary Core Ideas

- PS1-A, 2-PS1-2, PS3-C, ETS1-A, EST1-B

Time Required

- One or two class periods

Science and Engineering Practices

- Planning and carrying out investigations
- Analyzing and interpreting data
- Asking questions and defining problems

Cross Cutting Concepts

- Cause and effect
- Patterns

Objectives

At the end of the lesson, students will:

- Know the fundamental aspects of a solar panel and understand how placement and orientation affect its power output
- Be able to use the scientific method to isolate and adjust variables in a solar powered fountain
- Understand power measurement and energy concepts, using a small water pump
- Be able to use basic engineering, art and design skills to create a one-of-a-kind solar fountain

This activity guide was adapted from a prior REcharge lesson.

Reproduction Note: Reproduction of this activity guide is prohibited except for student use in the classroom. For permission to copy portions or all of this material for other purposes, please contact info@thegaleforce.org.

[Click to check out the NGSS Website, Full NGSS Standards, or Science and Engineering Practices in the NGSS](#)



Materials

There are many ways to construct a Solar Fountain. The guidebook suggests some ways using the basic materials below, but that's just the beginning of the design possibilities.

- Trays
- Plasticine
- Water pump
- Solar panel 3V 500mA (recommended size and power but doesn't need to be exactly that)
- Small Tube 1/8"
- Medium Tube 1/4"
- Large Tube 3/8"

You will need to supply the following materials:


- Scissors
- Water
- Towel
- Lamp (if you do not have good sunlight)
- High wattage incandescent bulb (100 watts or higher)
- Compact fluorescent bulb (optional)
- LED bulb (optional)
- Ruler
- Protractor
- Color acetate sheets (optional)
- Alternative fountain building material such as plastic bottles, large basins for water, more plasticine, straws, etc.

Guidance on purchasing materials:

[Click to look at tubing](#)

[Click to look at water pump](#)

REcharge Labs & KidWind have been leaders in K-12 renewable energy education for over 15 years. Their library of materials and programming are now a part of Gale Force Education. Gale Force Education is a non-profit focused on fostering opportunities for students, educators, and the public to explore a future powered by renewable energy.





Learning Goals

This activity demonstrates how solar energy is transformed into electricity that we can use. Students will use solar panels to power a small water pump and build a functioning fountain. In doing so, they will learn how a solar panel works, collect data and test variables, and apply their observations to their engineering process as they improve their designs.

Getting Ready

- Build and test your own Solar Fountain before the class begins. This is a valuable preview to the challenges and problems that students will face. Your example will also help students conceptualize the final product of the lesson.
- Gather the tools and any additional items students will need to complete the activity.
- If you are working inside, prepare a work area that can get wet, and set up a lamp in a spot that is safe from water. *Warning:* do not use water near electrical outlets! Prepare a pitcher of water. You will need towels for clean up.
- Part of this activity is best done outside on a sunny day, although it can be done indoors under some very high wattage lamps. If possible, plan to do this lesson during days predicted to be sunny. Cold weather does not harm the electronics or the solar panels, although it may be unpleasant when dealing with water!
- Gather some images of fountains from around the world. This will be helpful in starting the conversation with students on how to construct their fountains.
- Prepare the plasticine by warming it up. Since plasticine is an oil based clay that never hardens, it resists water absorption and will not dissolve or get gooey. It is easy to reuse and reshape plasticine as often as you like. But this also means that when the plasticine is cold, it is very difficult to mold. Warming the plasticine will make it much easier to use, especially for younger students. You can do this by placing the clay under the high wattage lamp (close but not touching it), by using a hair dryer, resting the plasticine on a radiator or heater, or by placing it in the sun. The plasticine will also soften the more it is handled. Once a desired shape is achieved, cold water can be run over the shape and the plasticine will harden quickly.

Activity


During the first part of this activity, students learn how to wire the solar panel to their pump to move water. During the second part, students perform experiments to better understand how their design affects the performance of their fountain. This activity works best with groups of two or three students.

Step 1: Beginning questions for students

- What is the most interesting or memorable fountain you have ever seen? Why does it stand out in your memory? What could it do? What made it unique?
- Who has seen solar panels before, and where?
- Why are solar panels important?
- What variables do you think affect how much power a solar panel produces?
- How do humans harness energy from the sun?

Step 2: Distribute materials

Each group of students will need: one solar panel, one pump, some plasticine, three sizes of tubing, two water trays, scissors, towel, pitcher of water, and lamp station.





Step 3: Affix the pump

Students should use the following instructions to attach the pump. Set up the solar fountain materials on a flat work area with a high wattage lamp. Set one tray into the other; this fortifies the tray's strength. Attach the pump to the middle of the tray using small pieces of plasticine like gum to stick the pump in place (Fig. A).

Step 4: Make a tube adapter

There are three tube sizes in the kit: small, medium, and large. In order for all three tube sizes to fit on the pump, an adapter needs to be made using the medium tube. To make the adapter, students should cut 1 inch off the medium tubing, and attach this piece to the nozzle on the pump. The fit should be snug (Fig. B). Now, test to see how the small and large tube sizes fit on the adapter (Fig C).

Step 5: Water pump and solar panel test

First, ask the students to make sure the adapter and tube fit tightly on the pump nozzle, starting with the small tube. The tubing will be too long to stand upright from the pump, and will need to be held upright by someone during testing.

Second, students should check to see that the pump is attached to the tray, and that the pump wires are hanging off the tray edge. Then, they should fill the tray with an inch of water, enough to cover the pump intake hole.

Third, they should attach the solar panel wires to the pump, red to red, and black to black. While it is attached to the pump, students should position the solar panel next to the lamp light (Fig. D). Water should be pumping up the tube. If it is not, students need to make sure all the wires are connected, that the water is above the pump intake hole, nothing is shading the panel, and the panel is close enough to the lamp. Students should work with the pump and the panel until water goes up the tube. Once the students have their system working, have them turn the lamp off and take a break to learn about the vocabulary and variables below.

Step 6: Vocabulary and variables

Many variables affect how much power the solar panel can produce, which in turn affects how much and how high water can be pumped. When designing a fountain, it is important to be familiar with certain vocabulary words and understand some of the important variables. The way these variables affect one another will influence how students design their fountains.

Fig. A




Fig. B




Fig. C





Fig. D





Solar panel (photovoltaics): Solar panels convert light into electricity. In this activity, the electricity generated by the solar panel powers the water pump. A solar panel is made up of tiny photovoltaic (PV) cells. Photovoltaic comes from the words photo, meaning light, and volt, the measurement of electricity. Because solar panels require light to generate electricity, the intensity and the angle of the light affects how much electricity can be generated.

Solar panel variables:

- light source
- distance from the light source
- angle of the panel to the light source

Light source: A light source is an object or device that glows or produces light. There are different kinds of light sources in the world, natural and human-made. The sun, fire, lightning, and glowing organisms are natural light sources. Human-made sources, like light bulbs, come in a variety of sizes, brightnesses, and types. Ask the students to name the types of lights located in the classroom, for example, fluorescent, incandescent, LED. If possible, try to define the wattage of the light bulbs, especially the one used in the lamp on the activity table.

Light source variables:

- type of light source
- wattage

Water pressure: Water pressure is the strength of water flow. In the example of solar fountains, if the water pressure is really high, the water will rise so high that it will overflow out of the top of the tube. If the water pressure is low, it will not rise very high in the tube.

Water pressure variables:

- solar panel electricity produced
- inside tube dimension

Indoors, this activity can be messy. Make sure lamp cords, power strips, and outlets, as well as any other devices using wall power, remain dry during the experiment. Water can cause electrical devices to malfunction, and in extreme cases, can cause lethal shock or fire.


Important: The solar panel included in the kit does not produce enough current to cause any shock or harm while submerged in water. It is safe for the pump to be completely submerged in water.

Step 7: Solar Scavenger Hunt

The Solar Scavenger Hunt demonstrates how the variables listed earlier will affect solar fountains. This is important to understand: if students can control energy flow, they can reliably predict how their fountain will behave and can make design decisions based on this. Distribute meter sticks, protractors, and copies of the Solar Scavenger Hunt worksheet at the end of this guide. Students will also need the pumps they set up earlier. This activity is best done in groups. One student will hold the tubing upright and position the solar panel. Another student will hold the meter stick and write down data (**Fig. E**).

First, identify a variety of light sources as a class. Encourage students to think about indoor and outdoor options. What are different types of light bulbs? Have the students list the light sources as they are discovered. For fun, prompt them to think about how additional variables affect the light, like colors from acetate sheets, reflective surfaces, shade, clouds or windows.

Fig. E



WARNING!

Keep water off wall powered electrical devices.